

PETROL GENERATOR

Powerlite

4.5kVA WITH RCD



Model	GPL045
Industry Rating	4.5kVA
Real Power	4000 Watts
Engine	Honda GX270
Fuel	Unleaded
Tank Capacity	6L
Fuel Usage	2.0L/Hour
Weight	58kg
Outlets	1 x 10A, 1 x 15A
Dimensions (LxWxH)	700mm x 500mm x 510mm

Powerlite 4.5kVA Petrol Generator

4000W Petrol Powerlite Generator, powered by a GX270 Honda engine with recoil start. Manufactured in Australia, the PH045 generator is mounted in a powder coated heavy duty compact roll frame. The Honda engine is paired with a Mecc Alte Alternator and is fitted with 1 x 10A and 1 x 15A outlet protected by an RCD.

Ideally suitable for portable electric tools, together with small machines, electric pump up to 1.1kW, lights and household appliances, provided that the total power consumption at any one time is less than 4000W.