

PETROL GENERATOR

6.0kVA WITH RCD

Powerlite



Model	GPL060
Industry Rating	6.0kVA
Real Power	5600 Watts
Engine	Honda GX340
Fuel	Unleaded
Tank Capacity	6.5L
Fuel Usage	2.5L/Hour
Weight	70kg
Outlets	1 x 10A, 1 x 15A
Dimensions (LxWxH)	760mm x 500mm x 540mm

Powerlite 6.0kVA Petrol Generator

5,600W Petrol Powerlite Generator, powered by Honda with recoil start. Manufactured in Australia, the PH060 generator is mounted in a powder coated heavy duty compact roll frame. The Honda engine is paired with a Mecc Alte Alternator and is fitted with 1 x 10A and 1 x 15A outlet protected by an RCD.

Its ideal use is to power portable electric tools, small machines, electric pump up to 1.5kW, air compressor, brick saw, pressure washer, lights and household appliances, provided that the total simultaneous power consumption at any one time is less than 5,600W.