## PETROL GENERATOR 8.0kVA WITH HIRE PACK



| Model              | GPL080HP              |
|--------------------|-----------------------|
| Industry Rating    | 8.0kVA                |
| Real Power         | 6800 Watts            |
| Engine             | Honda GX390           |
| Fuel               | Unleaded              |
| Tank Capacity      | 6.5L                  |
| Fuel Usage         | 2.5L/Hour             |
| Weight             | 73kg                  |
| Outlets            | 2 x 15A               |
| Dimensions (LxWxH) | 860mm x 500mm x 540mm |

## **Powerlite 8.0kVA Petrol Generator with Hire Pack**

6,800W Petrol Powerlite Generator, powered by a 13hp Honda engine recoil start with RCD and 2 weatherproof socket outlets. Manufactured in Australia the GPL080HP generator is mounted in a powder coated heavy duty wheel and handle frame and the Honda engine is paired with a Mecc Alte Alternator, giving it an industry rating of 8. This reliable generator fully complies to the Australian Standards and holds 6.5 litres of fuel and when being used at maximum power uses 2.5 litres of fuel per hour. This generator would be our best seller and ideally used for portable electric tools, 140 Amp welder (on light duty), shearing plant, air compressor (with up to 2.2kW electric motor), heaters, lights, appliances and excellent motor staring and welder performance, provided that the total power consumption at any one time is less than 6,800W.



P: 1300 255 266 E: sales@allcongroup.com.au W: allcongroup.com.au