

# PETROL GENERATOR

**Powerlite**

## 8.0kVA WITH RCD



Model	GPL080
Industry Rating	8.0kVA
Real Power	6800 Watts
Engine	Honda GX390
Fuel	Unleaded
Tank Capacity	6.5L
Fuel Usage	2.5L/Hour
Weight	73kg
Outlets	1 x 10A, 1 x 15A
Dimensions (LxWxH)	860mm x 500mm x 540mm

### Powerlite 8.0kVA Petrol Generator

6,800W Petrol Powerlite Generator, powered by a 13hp Honda engine recoil start with RCD and 2 weatherproof socket outlets. Manufactured in Australia the GPL080HP generator is mounted in a powder coated heavy duty wheel and handle frame and the Honda engine is paired with a Mecc Alte Alternator, giving it an industry rating of 8. This reliable generator fully complies to the Australian Standards and holds 6.5 litres of fuel and when being used at maximum power uses 2.5 litres of fuel per hour. This generator would be our best seller and ideally used for portable electric tools, 140 Amp welder (on light duty), shearing plant, air compressor (with up to 2.2kW electric motor), heaters, lights, appliances and excellent motor starting and welder performance, provided that the total power consumption at any one time is less than 6,800W.